



## D-I&- N

Dck Yf' =bgYfhYf'Zcf`GK A, / `GK A %\*



The SWM-PI Power Inserter is designed for use on the SWM-8 and SWM-16 DIRECTV switch.

- Frequency Range: 2-2150 MHz
- Insertion Loss: 1.5 dB typ.
- Input: 100~120Vac / 60Hz ~ 1.0 A
- Output: 29V / 1.3 A max / 37.7 W max
- Outputs: 1 IRD & 1 SWM
- Security: Double Insulated / Class II
- Fuse Protection: 250V / 2A (UL fuse)
- Power Cord: 2 pole polarized male plug / 1.8 m
- Connectors: "F" type (red colored to SWM)
- Environmental Requirements: Indoor Use Only
- Operating Temperature Range: 0 to 52C / 32 to 125F
- Dimensions: 5 5/8 x 2 x 2 1/4"
- The operating voltage light is located on the bottom part of the unit