

# OHM-QAMA-R01/R01A QAM A/C OmniHub % Modulator Module



## OHM j ° U ° -R01/R01A

R01 4 CH QAM A/C Modulator module

R01A 8 CH QAM A/C Modulator module



QAMA	
Output	4/8 frequencies via 1 RF female connector 75Ω
Standard	ITU-T J.83 Annex A/C
Frequency Range	47~862MHz
Bandwidth	6/7/8MHz
Constellation	16QAM/32QAM/64QAM/128QAM/256QAM
Symbol Rate	3.6~6.9 Ms/s
Output Level	Max. 105dBμV
MER	≥32dB
Power Consumption	4CH: Max. 23W; 8CH: Max. 27W