

: **5A** '? **]h**'%; <n: 5A 'GYf]Yg 5HYbi Uhcf DUXg

FAM-Kit

The FAM Kit is a selection of 10 each of the Toner FAM Series "F" type in line attenuators in the following values: 1, 2, 3, 6, 8, 10, 12, 16 & 20 dB.

 $Y \ \tilde{a} O \hat{b} O \tilde{b} \hat{A} \ \tilde{a} O \hat{A} [\ \mathring{A} \ \tilde{a} | \hat{A} | \hat{A} \ \tilde{a} | \hat{a} | \hat{a$







SPECIFICATIONS

MODEL	FAM-1	FAM-2	FAM-3	FAM-6	FAM-8	FAM-10	FAM-12	FAM-16	FAM-20
ATTENUATION (dB)									
5-600 MHz	0.9	2.2	2.7	5.6	7.5	9.6	11.5	15.8	19.4
600-750 MHz	1.0	2.1	3.4	6.3	8.2	10.6	12.5	16.5	19.8
750-900 MHz	1.1	2.2	3.4	6.3	7.8	10.6	12.5	16.5	19.3
900-1000 MHz	1.1	2.3	2.5	5.5	7.4	10.3	11.7	15.7	18.8
RETURN LOSS									
(dB) minimum									
5-600 MHz	24	23	23	26	26	22	22	26	20
600-750 MHz	22	21	21	24	22	21	21	22	19
750-900 MHz	18	18	20	22	20	20	20	20	18
900-1000 MHz	18	18	18	18	18	18	18	18	17