

**CATV QAM Channel Center Frequencies Annex B, 6 MHz Channels, 54-1002 MHz**

Channel Number	Center Frequency MHz	Channel Number	Center Frequency MHz	Channel Number	Center Frequency MHz	Channel Number	Center Frequency MHz
2	57	38	309	79	555	125	801
3	63	39	315	80	561	126	807
4	69	40	321	81	567	127	813
5	79	41	327	82	573	128	819
6	85	42	333	83	579	129	825
95	93	43	339	84	585	130	831
96	99	44	345	85	591	131	837
97	105	45	351	86	597	132	843
98	111	46	357	87	603	133	849
99	117	47	363	88	609	134	855
14	123	48	369	89	615	135	861
15	129	49	375	90	621	136	867
16	135	50	381	91	627	137	873
17	141	51	387	92	633	138	879
18	147	52	393	93	639	139	885
19	153	53	399	94	645	140	891
20	159	54	405	100	651	141	897
21	165	55	411	101	657	142	903
22	171	56	417	102	663	143	909
7	177	57	423	103	669	144	915
8	183	58	429	104	675	145	921
9	189	59	435	105	681	146	927
10	195	60	441	106	687	147	933
11	201	61	447	107	693	148	939
12	207	62	453	108	699	149	945
13	213	63	459	109	705	150	951
23	219	64	465	110	711	151	957
24	225	65	471	111	717	152	963
25	231	66	477	112	723	153	969
26	237	67	483	113	729	154	975
27	243	68	489	114	735	155	981
28	249	69	495	115	741	156	987
29	255	70	501	116	747	157	993
30	261	71	507	117	753	158	999
31	267	72	513	118	759		
32	273	73	519	119	765		
33	279	74	525	120	771		
34	285	75	531	121	777		
35	291	76	537	122	783		
36	297	77	543	123	789		
37	303	78	549	124	795		