

## JXP? ]h%2; <n JXP Style Pads

### JXP-Kit

The JXP Kit is a selection of 10 each of the Toner JXP Series Orange 1.1" Long Plug-In Pads in the following values: 1, 3, 6, 9, 12, 16, 18 & 20 dB



You will find a variety of JXP plug-in pads on hand to adjust signals in amplifiers as needed. The JXP pads are in a rugged 8" x 6" x 1-3/4" plastic storage box that features a clear lid so you can see the contents. The box has 10 compartments and a snap close lid to secure the JXP pads.



## JXP? ]h%2; <n JXP Style Pads

### Common Specifications

<b>Bandwidth</b>	5-1220 MHz
<b>Impedance</b>	75 Ω
<b>Return Loss</b>	>19 dB
<b>Size</b>	0.162" x 0.423" x 1.2" (D x W x L)

Model	Insertion Loss @ 50 MHz	Insertion Loss @ 860 MHz	Insertion Loss @ 1220 MHz
JXPEQ-2	2 ± 0.3 dB	0.8 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-3	3 ± 0.3 dB	1.1 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-4	4 ± 0.3 dB	1.2 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-5	5 ± 0.3 dB	1.5 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-6	6 ± 0.3 dB	1.7 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-7	7 ± 0.3 dB	2.1 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-8	8 ± 0.3 dB	2.3 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-9	9 ± 0.3 dB	2.5 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-10	10 ± 0.3 dB	2.7 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-11	11 ± 0.3 dB	3 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-12	12 ± 0.3 dB	3.3 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-13	13 ± 0.3 dB	3.5 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-14	14 ± 0.3 dB	3.7 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-15	15 ± 0.3 dB	4.2 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-16	16 ± 0.3 dB	4.6 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-17	17 ± 0.3 dB	5 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-18	18 ± 0.3 dB	5.3 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-19	19 ± 0.3 dB	6.5 ± 0.3 dB	0.75 ± 0.3 dB
JXPEQ-20	20 ± 0.3 dB	6.0 ± 0.3 dB	0.75 ± 0.3 dB