

CATV QAM Channel Center Frequency – 8 MHz

CC	Anaolgue MHz	Digital / COFDM	CATV / QAM MHz
E21	471.25	474	472
E22	479.25	482	480
E23	487.25	490	488
E24	495.25	498	496
E25	503.25	506	504
E26	511.25	514	512
E27	519.25	522	520
E28	527.25	530	528
E29	535.25	538	536
E30	543.25	546	544
E31	551.25	554	552
E32	559.25	562	560
E33	567.25	570	568
E34	575.25	578	576
E35	583.25	586	584
E36	591.25	594	592
E37	599.25	602	600
E38	607.25	610	608
E39	615.25	618	616
E40	623.25	626	624
E41	631.25	634	632
E42	639.25	642	640
E43	647.25	650	648
E44	655.25	658	656
E45	663.25	666	664
E46	671.25	674	672
E47	679.25	682	680
E48	687.25	690	688
E49	695.25	698	696
E50	703.25	706	704
E51	711.25	714	712
E52	719.25	722	720
E53	727.25	730	728
E54	735.25	738	736
E55	743.25	746	744
E56	751.25	754	752
E57	759.25	762	760
E58	767.25	770	768
E59	775.25	778	776
E60	783.25	786	784
E61	791.25	794	792
E62	799.25	802	800
E63	807.25	810	808
E64	815.25	818	816
E65	823.25	826	824
E66	831.25	834	832
E67	839.25	842	840
E68	847.25	850	848