

OHR-DVBS2FTA-00A DVB-S/S2 OmniHub 16 Receiving Module

OHR-DVBS2FTA-0

8 CH DVB-S2 receiving module, another interface card added on CR-DVBS2FTA-00, each module occupies 2 slots



DVB-S/S2	
Input	C/Ku Band, 8 channels via 8 RF female connectors
LNB Power	Independent power supplies for LNB-1 LNB-3, LNB-5 and LNB-7
LNB Voltage	13V/18V
LNB Current	Max. 400mA
Constellation	QPSK, 8PSK
Frequency Range	950~2150MHz
Signal Level	-70~-20dBm
Roll-off Factor	0.15, 0.20, 0.25, 0.35
Symbol Rate	DVB-S: 1~45Msps DVB-S2: 1~45Msps
FEC	DVB-S: 1/2, 2/3, 3/4, 5/6, 7/8 DVB-S2: 1/2, 3/5, 2/3, 3/4, 4/5, 5/6, 8/9, 9/10
Power Consumption	Max. 25W